



SSA-5000DP

PA AMPLIFIER with Built-in Digital Player











SSA-5000DP is a multi application PAAmplifier capable of delivering 500 Watts rated output. It has a built in high quality MP3 digital player with backlit LCD display. Features includes 7 Mic inputs, 2 Aux. inputs and RCA socket at the rear for CD/DVD player.

This amplifier is designed to give clean sound and reliable, trouble free operation under severe climatic conditions. Ideal for religious places, DJs and Music Shows, Public Meetings, Educational Institutions, and a variety of other PA applications.

Features:

- 7 Mic & 2 Aux Inputs.
- RCA socket for connecting CD player has been provided parallel to Aux-2 Jack.
- Built-in MP3 player with remote control, for USB, SD/MMC card.
- Preamplifier and Line Output for connecting to a Booster Amplifier.
- Line Input for connecting the output from any external mixer or another amplifier.
- Resettable circuit breaker for protection against overload and short circuit.
- Instant transfer to DC power (Car Battery) if AC power fails.
- Box Speaker/Driver Unit selector switch. Bass boost defeated at Driver Unit position for safer operation of driver units.

Specifications

POWER OUTPUT 750W Max., 500W RMS at 10% THD, 450W RMS at 5% THD, 415W RMS at 2% THD

OUTPUT REGULATION ≤ 2 dB, no load to full load at 1kHz

INPUT CHANNELS 7 × Mic 0.8mV/4.7k Ω , 2 × Aux 100mV/470 k Ω , 1 × CD 200mV/50 k Ω , 1 × Line 1V/50k Ω

50-15,000Hz ±3dB FREQUENCY RESPONSE

SIGNAL TO NOISE RATIO 60dB

TONE CONTROLS Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz

OUTPUT Preamp 200mV/600 Ω , Line 1V/1k Ω

SPEAKER OUTPUT 4Ω, 8Ω, 70V & 100V

DIGITAL PLAYER MP3 Player with USB, SD and MMC Card Reader **POWER SUPPLY** AC: 220-240V 50/60Hz DC: 36V (3×12V Car Battery)

POWER CONSUMPTION AC: 1000VA DC: 8A **DIMENSIONS** W510 × H172 × D385 mm

WEIGHT 27.0kg

> Design and Specifications are subject to change without notice owing to continuous product up-gradation. Technical specifications are subject to production tolerances. We cannot be held responsible for printing errors, should they occur. AND as a registered trademark of Ahuja Radios in India and other countries.
>
> © Copyright Ahuja Radios, 2015. All rights reserved. Any unauthorized reproduction or use of logos, images or design elements is strictly prohibited by law. No part of this compilation may be reproduced in any manner or translated without written permission.