
## APM-202CU **Control Unit**







- APM-202CU is a rack mounting switcher / control unit which works with APM-201RM and upto 2 amplifiers to form a 6 zone zonal paging system with multi level priority and switchable background music.
- 6 Zone Switcher / Paging Control Unit for use with APM-201RM.
- 6 Zone Selector switches, plus ALL CALL switch.
- Provision for two 100V input signals, one for speech and one for background music.
- Priority of speech over background music.
- Provision for routing background music source to selected zones.
- Provision to make announcements from the control unit.
- Status monitoring of all zones.

- Provision for emergency trigger input and alarm input with highest priority.
- Standard 19" rack mounting chassis.

| SPECIFICATIONS         |  |
|------------------------|--|
| SWITCHING SIGNAL LEVEL | 100V (Nominal)                                       |
| INPUTS (Nominal)       | 3 x APM-201RM (1V/10k balanced), 1 x Mic (1mV/4.7k), |
|                        | Speech Amp (100V), Music Amp (100V), Alarm (100mV).  |
| SWITCHES               | 6 Zone Selector switches, All Call, Chime, Reset,    |
|                        | Music/Call Selector, Power ON/OFF.                   |
| CONTROLS               | Mic Level, Chime level, Alarm level                  |
| POWER SUPPLY           | AC 220-240V, 50/60Hz; DC 24V (2 x 12V Car Battery)   |
| DIMENSIONS             | W483 × H75 × D300                                    |
| WEIGHT                 | 4.8kg  |