


Ahuja introduces a 400 Watts Professional 2-Way PA Speaker System with Exceptional Efficiency, long through and Unmatched Intelligible Sound.

- Two 15" High Performance LF Transducers and a High Frequency Compression Horn Driver housed in an acoustically treated Bass Reflex enclosure with ultra-modern paint finish.
- Sturdy and Aesthetically Designed Metal Grill lends both protection to the speakers as well as superb looks to the cabinet.
- Well designed heavy duty metal handles ensure hassle-free mobility and transportation.
- Suitable for both indoor and outdoor sound reinforcement applications Ideal for Auditoria... DJs... Live performances... etc
- **AHUJA** logo engraved on both sides of the cabinet lends uniqueness & freshness to the design and makes it difficult to imitate.

### Specifications

INPUT POWER	400W RMS
CONFIGURATION	Two Way
FREQUENCY RESPONSE	50-20,000Hz
COMPONENTS	2 × 15" LF Speaker 4" × 10" Dynamic HF Unit
SPL (1W/1m)	101dB
MAX. RATED SPL	127dB
NOMINAL IMPEDANCE	8Ω
CROSSOVER FREQUENCY	6kHz
PORT	Free Flow Flared
INPUT CONNECTORS	2 Nos. of Speakon Sockets
DIMENSIONS	W530 × H1210 × D510mm
WEIGHT	65.00kg



400  
WATTS

2  
WAY

Design and Specifications are subject to change without notice owing to continuous product up-gradation. Technical specifications are subject to production tolerances. We cannot be held responsible for printing errors, should they occur. AHUJA is a registered trademark of Ahuja Radios in India and other countries. © Copyright Ahuja Radios, 2019. All rights reserved. Any unauthorized reproduction or use of logos, images or design elements is strictly prohibited by law. No part of this compilation may be reproduced in any manner or translated without written permission.

**AHUJA RADIOS**

E. & O. E. 3K/11/16

215, Okhla Industrial Estate, New Delhi - 110 020, INDIA Tel.: +91-11-26831549, 41612474 Fax: +91-11-26847287  
E-mail: marketing@ahujaradios.com Website: www.ahujaradios.com